

Mixer y Switchers

Switcher HD de 6 entradas rackeable**SE-1200MU**

| | |
|------------------------------------|--|
| Video Standard | HD |
| Video Format | 1080i 50/59.94/60Hz 720p 50/59.94/60Hz |
| Video Processing | SDI: 4:2:2 HDMI: YUV 4:2:2 10 bit, RGB 4:4:4 |
| Input Routable / Crosspoint | All 6, repeatable |
| Video Input | 4x HD-SDI 2x HDMI (RGB/YUV, 1080i/1080p/720p) |
| Mix HD & SD Source | ---- |
| Computer Graphic Interface | 2 via HDMI |
| Video Output | 2x HD-SDI 2x HDMI assignable: PGM(w/DSK 1&2), PGM(w/DSK 1), PGM Clean, PVW(w/o DSK), multi-view, Input 1-6 |
| Down-converted Output | ---- |
| Built-in Multi-view Monitoring Out | HDMI & SDI assignable, Ethernet (MJPEG) |
| Analogue Audio Input | 2x Balanced XLR |
| Analogue Audio Output | ---- |
| Digital Embedded Audio Support | Input 2 channels, Output 2 channels |
| Audio Delay Calibration | ---- |
| A+V Switching | Yes |
| Chromakey | 2 |
| Title Creator | ---- |
| USK | 2x Keyer support Chromakey/ Linear/ Luma Key |
| DSK | 2x DSK support Lumakey/ Linear key (Key / Fill) |
| Picture in Picture | 1 |
| Logo Insertion | ---- |
| Still Store | 500 |
| Effects | FTB, Cut, 32 Wipe with border |
| Transition Preview | Full transitions preview |
| Sync / Reference In/Out | Built-in Genlock (internal) |
| Tally Output | 1x D-sub 15pin, dual color |
| PC Remote Control | Ethernet (free Window software) RS-422/ RS-232 |
| Built-in Audio Mixer | ---- |

| | |
|-----------------------|---|
| Special Features | Motion JPEG Multi-view streaming (120 memory preset, BGD Transition on/off option) Free Virtual Set and Stinger transition included |
| Chassis | 1RU rack-mount mainframe |
| Dimension (LxWxH) | 440 x 215 x 49 mm |
| Weight | 1.5 kg |
| Power | DC 12V, 19W |
| Operating Temp. Range | 0~40 °C |
| What's in the Box | 1 x SE-1200MU product 1 x AD Switch DC 12V 1 x DB9P TO DB9P Cable 2 x 1U Rack Mount Ear 6 x M4 Screws for Rack Mount Ear |