

Switchers - Mixer

HD 8-Channel Digital Video Switcher**SE-2600MU**

| | |
|------------------------------------|--|
| Video Standard | Full HD |
| Video Format | <p>Input: 1080p 50/ 59.94/ 60Hz 1080i 50/ 59.94/ 60Hz 720p 50/ 59.94/ 60Hz</p> <p>Output: 1080p 50/ 59.94/ 60Hz 1080i 50/ 59.94/ 60Hz 720p 50/ 59.94/ 60Hz</p> |
| Video Processing | SDI: 4:2:2 HDMI: YUV 4:2:2, RGB: 4:4:4 |
| Input Routable / Crosspoint | YES |
| Video Input | Total 8 live inputs 4 x SDI 4 x HDMI |
| Mix HD & SD Source | ---- |
| Computer Graphic Interface | 4 via HDMI |
| Video Output | 3 x SDI 3 x HDMI assignable: Multiview, PGM, PVW, PGM+DSK, Clean PGM, Clean PVW, Input 1-8, STILL 1, STILL 2, Flex source |
| Down-converted Output | 1x SDI |
| Built-in Multi-view Monitoring Out | HDMI & SDI assignable |
| Analogue Audio Input | 2x Balanced Mini XLR |
| Analogue Audio Output | ---- |
| Digital Embedded Audio Support | SDI Input/Output 4 channels, HDMI Input/Output 2 channels |
| Audio Delay Calibration | Up to 16 fields or 8 frames per channel |
| A+V Switching | Yes |
| Chromakey | 4 |
| Title Creator | Yes |
| USK | 4x Keyer support Chromakey/ Linear/ Luma Key |
| DSK | 2x DSK support Lumakey & Linear key (Key / Fill) |
| Picture in Picture | 4 |
| Logo Insertion | 2 |
| Still Store | 999+ (1080p) |
| Effects | Cut, Auto, WIPE, Mix |

| | |
|-------------------------|---|
| Transition Preview | Full transitions preview |
| Sync / Reference In/Out | 1 x BNC Ref in 1 x BNC Ref out (loop-through) |
| Tally Output | 1x D-sub 25pin, dual color |
| PC Remote Control | RS-232 / DVIP (Ethernet) |
| Camera Control | ---- |
| Built-in Audio Mixer | ---- |
| Storage | ---- |
| Recording File System | ---- |
| Recording File Format | ---- |
| Video Encode | ---- |
| Audio Encode | ---- |
| Streaming Protocol | ---- |
| Firmware Update | USB |
| Special Features | User Memory Preset Free Virtual Set and Stinger transition included |
| Chassis | Unibody |
| Dimension (LxWxH) | 483.60*223*44 mm |
| Weight | 3.4 kg |
| Power | DC 12V, 82W |
| Operating Temp. Range | 0~40 °C |
| What's in the Box | 1 x SE-2600MU product 1 x AD Switch DC 12V 1 x AC Cord 4 x M5 Screws for Rack Mount Ear 2 x Mini XLR 3P-F to XLR 3P-F Cable |