

Teleprompter

19" Studio Teleprompter Kit with Dual Mount Options

TP-750

Device Used	19" LED monitor
Camera-Mount Interface	Prompter Rail
Smartphone / Tablet Size	N/A
Supported Languages	Unicode - All languages supported
Hood Dimension / Prompter Size	Width: 470mm Height: 390mm Depth: 870mm
LCD Native Resolution	1280 x 1024
LCD Brightness	1000 NIT
Remote Control	WR-600 (Included) WR-500 FS-30
Weight	9.8Kg
Operating Temp. Range	0~40 °C
Power	12V DC (Mains adapter supplied)
Carry Case Dimensions (excluding handle)	N/A

What's in the Box

1 x Main TP-750 ENG prompter rail
1 x Smaller rail with spacer block for mounting item
2 x C ¼" Screws, Length 27mm, secures item A or AA to B
1 x D WR-600 USB remote and USB cable
1 x Hex Tool (Silver) for counter sunk Hex head screws
1 x Hex Tool (Silver) for Glass Frame Hex screws
1 x Hex Tool (Silver) for VESA Hex screws
2 x 16mm ¼ screws with a washer to attach item F to item B (With red dot)
1 x 19" LED Monitor
1 x Glass frame with 4 Velcro straps
2 x Wing nut screws ¼" Length 19mm secures item A or AA to G
1 x Cloth Snood/Hood with Velcro straps
1 x 70/30 Glass sheet with Green and Red stickers
1 x Snood/Hood support wire
2 x L ¼" Camera securing screws, length 16mm
1 x ¼" Camera securing screws, length 20mm (to be used with item N)
2 x M ¼" Camera securing screws, length 31mm
1 x N Camera riser block 15mm thick
4 x Round head Allen screw 7/8", 2 pcs to attach item N to NN2 or AB,
2 pcs to attach item AB to B.
1 x Additional riser block (pre-attached to Item AA upon shipment with two ¾" screws)
4 x Round head Allen screws 5/16" to attach item O to B and optional LTC-45, LTC clock
1 x Mounting bracket to attach the optional LTC clock to item B
1 x P Adapter screw to convert 3/8" hole to ¼" hole
3 x ¼" Counter sunk hex head screw length 5/8", one for camera securing to A, two for B to F
1 x ¼" Counter sunk hex head screw, length 1 ¼" long for camera securing to A and N
1 x Talent monitor vertical mounting rail
1 x Talent monitor VESA adapter plate
4 x 14mm M4 screws for mounting 75MM VESA monitors
1 x Universal mains PSU 12V/4A
2 x BNC Male to Female HD-SDI cable
2 x ¼" Counter sunk hex head screw length 7/8", to attach to Item Y to N 2
1 x Quick-release plate
2 x 12mm M4 Screws to secure item J
1 x Small rail to attach item G to B in a freestanding configuration
1 x Additional riser block or attach to item to A
2 x 16MM M5 screw to attach item S to item B
4 x 8mm M4 screws for mounting item T
4 x 12mm M4 screws for mounting item 100MM VESA monitors