Teleprompter

19” Studio-Teleprompter-Kit mit dualen Montageoptionen

TP-750

Device Used	19” LED monitor
Camera-Mount Interface	Prompter Rail
Smartphone / Tablet Size	N/A
Supported Languages	Unicode – All languages supported
Hood Dimension / Prompter Size	Width: 470mm Height: 390mm Depth: 870mm
LCD Native Resolution	1280 x 1024
LCD Brightness	1000 NIT
Remote Control	WR-600 (Included) WR-500 FS-30
Weight	9.8Kg
Operating Temp. Range	0~40 °C
Power	12V DC (Mains adapter supplied)
Carry Case Dimensions (excluding handle)	N/A

What's in the Box	1 x Main TP-750 ENG prompter rail 1 x Smaller rail with spacer block for mounting item 2 x C ¼” Screws, Length 27mm, secures item A or AA to B 1 x D WR-600 USB remote and USB cable 1 x Hex Tool (Silver) for counter sunk Hex head screws 1 x Hex Tool (Silver) for Glass Frame Hex screws 1 x Hex Tool (Silver) for VESA Hex screws 2 x 16mm ¼ screws with a washer to attach item F to item B (With red dot) 1 x 19” LED Monitor 1 x Glass frame with 4 Velcro straps 2 x Wing nut screws ¼” Length 19mm secures item A or AA to G 1 x Cloth Snood/Hood with Velcro straps 1 x 70/30 Glass sheet with Green and Red stickers 1 x Snood/Hood support wire 2 x L ¼” Camera securing screws, length 16mm 1 x ¼” Camera securing screws, length 20mm (to be used with item N) 2 x M ¼” Camera securing screws, length 31mm 1 x N Camera riser block 15mm thick 4 x Round head Allen screw 7/8”, 2 pcs to attach item N to NN2 or AB, 2 pcs to attach item AB to B. 1 x Additional riser block (pre-attached to Item AA upon shipment with two ¾” screws) 4 x Round head Allen screws 5/16” to attach item O to B and optional LTC-45, LTC clock 1 x Mounting bracket to attach the optional LTC clock to item B 1 x P Adapter screw to convert 3/8” hole to ¼” hole 3 x ¼” Counter sunk hex head screw length 5/8”, one for camera securing to A, two for B to F 1 x ¼” Counter sunk hex head screw, length 1 ¼” long for camera securing to A and N 1 x Talent monitor vertical mounting rail 1 x Talent monitor VESA adapter plate 4 x 14mm M4 screws for mounting 75MM VESA monitors 1 x Universal mains PSU 12V/4A 2 x BNC Male to Female HD-SDI cable 2 x ¼” Counter sunk hex head screw length 7/8”, to attach to Item Y to N 2 1 x Quick-release plate 2 x 12mm M4 Screws to secure item J 1 x Small rail to attach item G to B in a freestanding configuration 1 x Additional riser block or attach to item to A 2 x 16MM M5 screw to attach item S to item B 4 x 8mm M4 screws for mounting item T 4 x 12mm M4 screws for mounting item 100MM VESA monitors