

Auto Switchers

Steuerungsschnittstelle des Voice Tracking

VoiceTRX100

| | |
|-----------------------------------|---|
| Control | Web browser UI for configuration and control DVIP commands |
| Protocol | DVIP |
| Network Feature | 1x RJ-45 Female (10/100/1000M Ethernet) DHCP/Static IP |
| POE | IEEE 802.3at PoE+ |
| F/W Update | Automatic firmware upgrade |
| Power | Input AC 100~240V Switching Adaptor Output DC 12V / 1A |
| Video Output | 2 x HDMI 2.0 |
| Supported Video Outout Resolution | Up to 3840x2160p 60 |
| Supported Video Switchers | iCast 10NDI series KMU-100+ SE-650 SE-1200MU SE-2600 series SE-3200 series SE-4000 series |

Supported
Microphones/Audio Mixer

Ai Speech MC-10A
Audio-Technica ATND1061
Audio-Technica ATUC-IR
Audio-Technica ATUC-50
Bosch DICENTIS Wireless
Bosch CCS-1000D
Relacart ACM-335
Relacart ACM-582
Sennheiser TCCM
Sennheiser TCC2
Shure MXW Microflex
Shure MXA-910
Shure MXA-920

USB Audio Mixers / Interfaces:

Allen and Heath CQ12T
Allen and Heath CQ18T
Zoom LiveTrak L6
Zoom LiveTrak L6 Max
Zoom LiveTrak L8
Zoom LiveTrak L12
RodeCaster Pro II
SoundCraft UI24R
M-Audio Duo
M-Audio Air 192|14
Tascam US-16X08
Tascam Mixcast 4
Behringer UMC404HD
Yamaha MGX12
Yamaha MGX16
Yamaha TF1 / TF3 / TF5
Yamaha DM3 / DM3S
Yamaha DM7 / DM7C