Automatisierungs-Controller

# Steuerungsschnittstelle des Voice Tracking

**VoiceTRX50**

| | |
|---|---|
| Control | Web browser UI for configuration and control<br>DVIP commands |
| Protocol | DVIP |
| Network Feature | 1x RJ-45 Female (10/100/1000M Ethernet) DHCP/Static IP |
| POE | IEEE 802.3at<br>PoE+ |
| F/W Update | Automatic firmware upgrade |
| Power | Input AC 100~240V Switching Adaptor<br>Output DC 12V / 1A |
| Video Output | 2 x HDMI 2.0 |
| Supported Video Outout Resolution | Up to 3840x2160p 60 |
| Supported Video Switchers | iCast 10NDI series<br>KMU-100+<br>SE-650<br>SE-1200MU<br>SE-2600 series<br>SE-3200 series<br>SE-4000 series |
| Supported Microphones/Audio Mixer | Allen and Heath CQ12T<br>Allen and Heath CQ18T<br>Zoom LiveTrak L6<br>Zoom LiveTrak L6 Max<br>Zoom LiveTrak L8<br>Zoom LiveTrak L12<br>RodeCaster Pro II<br>SoundCraft UI24R<br>M-Audio Duo<br>M-Audio Air 192\|14<br>Tascam US-16X08<br>Tascam Mixcast 4<br>Behringer UMC404HD<br>Yamaha MGX12<br>Yamaha MGX16<br>Yamaha TF1 / TF3 / TF5<br>Yamaha DM3 / DM3S<br>Yamaha DM7 / DM7C |