

Mixer y Switchers

Conmutador de video digital HD de 8 canales

SE-2600

Video Standard	Full HD
Video Format	Input: 1080p 50/ 59.94/ 60Hz 1080i 50/ 59.94/ 60Hz 720p 50/ 59.94/ 60Hz Output: 1080p 50/ 59.94/ 60Hz 1080i 50/ 59.94/ 60Hz 720p 50/ 59.94/ 60Hz
Video Processing	SDI: 4:2:2 HDMI: YUV 4:2:2, RGB: 4:4:4
Input Routable / Crosspoint	YES
Video Input	Total 8 live inputs 4 x SDI 4 x HDMI
Mix HD & SD Source	----
Computer Graphic Interface	4 via HDMI
Video Output	3 x SDI 3 x HDMI assignable: Multiview, PGM, PVW, PGM+DSK, Clean PGM, Clean PVW, Input 1-8, STILL 1, STILL 2, Flex source
Down-converted Output	---
Built-in Multi-view Monitoring Out	HDMI & SDI assignable
Analogue Audio Input	2 x XLR/MIC (6.3mm) Combo Socket 1 x Stereo RCA set (L/R)
Analogue Audio Output	1 x Stereo RCA set (L/R)
Digital Embedded Audio Support	SDI Input/Output 4 channels, HDMI Input/Output 2 channels
Audio Delay Calibration	Up to 16 fields or 8 frames per channel
A+V Switching	Yes
Chromakey	4
Title Creator	Yes
USK	4x Keyer support Chromakey/ Linear/ Luma Key
DSK	2x DSK support Lumakey & Linear key (Key / Fill)
Picture in Picture	4
Logo Insertion	2
Still Store	999+ (1080p)

Effects	Cut, Auto, WIPE, Mix, DVE, Stinger
Transition Preview	Full transitions preview
Sync / Reference In/Out	1 x BNC Ref in 1 x BNC Ref out (loop-through)
Tally Output	1x D-sub 25pin, dual color
PC Remote Control	RS-232 / DVIP (Ethernet)
Camera Control	----
Built-in Audio Mixer	----
Storage	----
Recording File System	----
Recording File Format	----
Video Encode	----
Audio Encode	----
Streaming Protocol	----
Firmware Update	USB
Special Features	User Memory Preset Free Virtual Set and Stinger transition included
Chassis	Unibody
Dimension (LxWxH)	431*313.2*84 mm
Weight	3.8 kg
Power	DC 12V, 82W
Operating Temp. Range	0~40 °C
What's in the Box	1 x SE-2600 product 1 x AD Switch DC 12V 1 x AC Cord