

Mixer y Switchers

Switcher digital SD de 4 canales

SE-500

Video Standard	SD
Video Format	NTSC 480i 59.94Hz PAL 576i 50Hz
Video Processing	SDI: 4:2:2
Input Routable / Crosspoint	Fixed
Video Input	4x CV or 4x Y/C
Mix HD & SD Source	----
Computer Graphic Interface	----
Video Output	2x CV & 1x Y/C or 1x CV & 1x YUV 1x CV Quad PVW
Down-converted Output	----
Built-in Multi-view Monitoring Out	1x CV
Analogue Audio Input	2x ¼" Mic jack 2x Unbalanced RCA (pair)
Analogue Audio Output	2x Unbalanced RCA (pair)
Digital Embedded Audio Support	----
Audio Delay Calibration	----
A+V Switching	----
Chromakey	----
Title Creator	----
USK	----
DSK	----
Picture in Picture	1
Logo Insertion	----
Still Store	----
Effects	Quad, Split, 11 Wipe with border
Transition Preview	Yes
Sync / Reference In/Out	Built-in Genlock (internal)
Tally Output	1x D-sub 15pin, dual color
PC Remote Control	Via RS-232
Built-in Audio Mixer	3 channels
Special Features	----
Chassis	Unibody
Dimension (LxWxH)	398 x 260 x 82 mm

Weight	2.2 kg
Power	DC 12V 18W
Operating Temp. Range	0~40 °C
What's in the Box	1 x SE-500 product 1 x AD Switch DC 12V 2 x BNC to RCA Connector 1 x YUV (BNCx3 to S+BNC) Cable