

Mixer y Switchers

4 canales de 1080p HDMI switcher de vídeo SE-500HD

| | |
|------------------------------------|---|
| Video Standard | Full HD & SD |
| Video Format | 1080p 50/59.94/60Hz 1080i 50/59.94/60Hz 720p 50/59.94/60Hz 576i 50Hz 480i 59.94Hz |
| Video Processing | HDMI: YUV 4:4:4 10 bit, RGB: 4:4:4 |
| Input Routable / Crosspoint | ---- |
| Video Input | 4x HDMI |
| Mix HD & SD Source | Yes |
| Computer Graphic Interface | 4 via HDMI |
| Video Output | 2 x HDMI (1 is MV, 1 is PGM) |
| Down-converted Output | Yes |
| Built-in Multi-view Monitoring Out | HDMI |
| Analogue Audio Input | 1 x Stereo RCA (L/R) 2 x Mono Microphone |
| Analogue Audio Output | 1 x Stereo RCA (L/R) 1 x Stereo headphone (Mini Jack with volume control) |
| Digital Embedded Audio Support | Input 2 channels, Output 2 channels |
| Audio Delay Calibration | ---- |
| A+V Switching | Yes |
| Chromakey | ---- |
| Title Creator | ---- |
| USK | Lumakey |
| DSK | ---- |
| Picture in Picture | 1 |
| Logo Insertion | ---- |
| Still Store | ---- |
| Effects | FTB, Cut, Wipe with border |
| Transition Preview | ---- |
| Sync / Reference In/Out | Built-in Genlock (internal) |
| Tally Output | 1x D-sub 15pin, dual color |
| PC Remote Control | ---- |
| Camera Control | ---- |
| Built-in Audio Mixer | Yes, 4 channels |

| | |
|-----------------------|---|
| Storage | ---- |
| Recording File System | ---- |
| Recording File Format | ---- |
| Video Encode | ---- |
| Audio Encode | ---- |
| Streaming Protocol | ---- |
| Firmware Update | USB |
| Special Features | Built-in video scaler for mixed resolution inputs |
| Chassis | Unibody |
| Dimension (LxWxH) | 400 x 250 x 82 mm |
| Weight | 1.7 kg |
| Power | DC 12V, 29W |
| Operating Temp. Range | 0~40 °C |
| What's in the Box | 1 x SE-500HD product 1 x AD Switch DC 12V with AC Cord |