

Datavideo Product Compare

<https://datavideo.com/kr/>

모델 넘버	TP-700
제품	유니버설 15인치 스튜디오 텔레프롬프터 – 표준형 및 독립형 구성
Device Used	15" monitor with integrated dvPrompter Plus software
Camera-Mount Interface	Prompter Rail
Smartphone / Tablet Size	N/A
Supported Languages	Unicode – All languages supported
Prompter Size (Max)	Width: 430mm Height: 345mm Depth: 820mm
LCD Native Resolution	1024x768
LCD Brightness	350 NIT
Remote Control	* Monitoring and control via LAN *Optional WR-500 wired hardware remote or FS-30 Foot Pedal *Supports generic presentation remote controls with USB receivers
Weight	6.3 Kg
Operating Temp. Range	0~40 °C
Power	12V DC (Mains adapter supplied) V-Lock battery PoE (optional adapter required)

Carry Case Dimensions (excluding handle)	N/A
What's in the Box	<p>1 x Main TP-700 ENG prompter rail</p> <p>1 x Smaller rail with spacer block for mounting item F</p> <p>2 x $\frac{1}{4}$" Screws Length 27mm secures item A or AA to B</p> <p>1 x Hex Tool (Silver) for counter sunk Hex head screws</p> <p>1 x Hex Tool (Silver) for Glass Frame Hex screws</p> <p>1 x Hex Tool (Silver) for VESA Hex screws</p> <p>2 x 16mm $\frac{1}{4}$ screws with washer to attach item F to item B (With red dot)</p> <p>1 x 15" LCD control unit 1</p> <p>1 x Glass frame with 4 Velcro straps</p> <p>2 x Wing nut screws $\frac{1}{4}$" Length 19mm secures item A or AA to G</p> <p>1 x Cloth Snood/Hood with Velcro straps</p> <p>1 x 70/30 Glass sheet with Green and Red stickers</p> <p>1 x Snood/Hood support wire</p> <p>2 x $\frac{1}{4}$" Camera securing screws length 16mm</p> <p>2 x $\frac{1}{4}$" Camera securing screws length 31mm</p> <p>1 x Camera riser block 15mm thick</p> <p>1 x USB Mouse</p> <p>1 x Adapter screw to convert 3/8" hole to $\frac{1}{4}$" hole</p> <p>1 x $\frac{1}{4}$" Counter sunk hex head screw length 16mm</p> <p>1 x $\frac{1}{4}$" Counter sunk hex head screw length 31mm</p> <p>1 x Talent monitor vertical mounting rail</p> <p>1 x Talent monitor VESA adapter plate</p> <p>4 x 14mm M4 screws for mounting 75MM VESA monitors</p> <p>1 x Universal mains PSU</p> <p>1 x Ethernet Cable 5M</p> <p>1 x 3.5mm input adapter for WR-500 remote control</p> <p>1 x 12V D-Tap Cable</p> <p>2 x 12mm M4 Screws to secure item J</p> <p>1 x Small rail to attached item G to B in a freestanding configuration</p> <p>2 x 16MM M4 screw to attach item S to item B</p> <p>4 x 8mm M4 screws for mounting item T</p> <p>4 x 12mm M4 screws for mounting item 100MM VESA monitors</p>