

Mixer y Switchers

4 canales de 1080p HDMI switcher de vídeo SE-500HD

Video Standard	Full HD & SD
Video Format	1080p 50/59.94/60Hz 1080i 50/59.94/60Hz 720p 50/59.94/60Hz 576i 50Hz 480i 59.94Hz
Video Processing	HDMI: YUV 4:4:4 10 bit, RGB: 4:4:4
Input Routable / Crosspoint	----
Video Input	4x HDMI
Mix HD & SD Source	Yes
Computer Graphic Interface	4 via HDMI
Video Output	2 x HDMI (1 is MV, 1 is PGM)
Down-converted Output	Yes
Built-in Multi-view Monitoring Out	HDMI
Analogue Audio Input	1 x Stereo RCA (L/R) 2 x Mono Microphone
Analogue Audio Output	1 x Stereo RCA (L/R) 1 x Stereo headphone (Mini Jack with volume control)
Digital Embedded Audio Support	Input 2 channels, Output 2 channels
Audio Delay Calibration	----
A+V Switching	Yes
Chromakey	----
Title Creator	----
USK	Lumakey
DSK	----
Picture in Picture	1
Logo Insertion	----
Still Store	----
Effects	FTB, Cut, Wipe with border
Transition Preview	----
Sync / Reference In/Out	Built-in Genlock (internal)
Tally Output	1x D-sub 15pin, dual color
PC Remote Control	----
Camera Control	----
Built-in Audio Mixer	Yes, 4 channels

Storage	----
Recording File System	----
Recording File Format	----
Video Encode	----
Audio Encode	----
Streaming Protocol	----
Firmware Update	USB
Special Features	Built-in video scaler for mixed resolution inputs
Chassis	Unibody
Dimension (LxWxH)	400 x 250 x 82 mm
Weight	1.7 kg
Power	DC 12V, 29W
Operating Temp. Range	0~40 °C
What's in the Box	1 x SE-500HD product 1 x AD Switch DC 12V with AC Cord