

Auto Switchers

# Interfaz de control de seguimiento por voz

## VoiceTRX50

Control	Web browser UI for configuration and control DVIP commands
Protocol	DVIP
Network Feature	1x RJ-45 Female (10/100/1000M Ethernet) DHCP/Static IP
POE	IEEE 802.3at PoE+
F/W Update	Automatic firmware upgrade
Power	Input AC 100~240V Switching Adaptor Output DC 12V / 1A
Video Output	2 x HDMI 2.0
Supported Video Outout Resolution	Up to 3840x2160p 60
Supported Video Switchers	iCast 10NDI series KMU-100+ SE-650 SE-1200MU SE-2600 series SE-3200 series SE-4000 series
Supported Microphones	Allen and Heath CQ12T Allen and Heath CQ18T Zoom LiveTrak L6 Zoom LiveTrak L6 Max Zoom LiveTrak L8 Zoom LiveTrak L12 RodeCaster Pro II SoundCraft UI24R M-Audio Duo M-Audio Air 192 14 Tascam US-16X08 Tascam Mixcast 4 Behringer UMC404HD Yamaha MGX12 Yamaha MGX16 Yamaha TF1 / TF3 / TF5 Yamaha DM3 / DM3S Yamaha DM7 / DM7C