Audio Mixing and Management

## 6-Channel Audio Delay/Mixer with Level Adjustment AD-200

	·
Audio Input	6x XLR, 2x RCA
Audio Output	4x XLR, 2x RCA, 1x 3.5mm
Audio Indicator	1.77" Color OLED
Audio Delay	Up to 3000ms
Audio Sample Rates	48 KHz
Special Feature	Audio Delay and Mix, delay by channel
Chassis	2 units, rack-mount mainframe
Power	DC 12V 19W (front) DC 12V 16W (rear)
Dimension (LxWxH)	440 x 126 x 42 mm
Weight	1.8 kg
Operating Temp. Range	0~40 °C
What's in the Box	1 x AD-200 main unit 1 x AD-200 control unit 1 x AD Switch DC 12V 1 x D-SUB cable, Male to MALE,Cable 1 x 3.5mm Stereo Cable, 1.2m 4 x 1U rack kit 16 x Screws M4 x 8mm