## **Datavideo Product Compare**

https://datavideo.com/my/

| Model<br>Number             | AD-200  |
|-----------------------------|---|
| Product                     | 6-Channel Audio Delay/Mixer with Level Adjustment |
| Audio Input                 | 6x XLR, 2x RCA                                    |
| Audio<br>Output             | 4x XLR, 2x RCA, 1x 3.5mm                          |
| Audio<br>Indicator          | 1.77" Color OLED                                  |
| Audio Delay                 | Up to 3000ms                                      |
| Audio<br>Sample<br>Rates    | 48 KHz  |
| Special<br>Feature          | Audio Delay and Mix, delay by channel             |
| Chassis                     | 2 units, rack-mount mainframe                     |
| Power                       | DC 12V 19W (front) DC 12V 16W (rear)              |
| Dimension<br>(LxWxH)        | 440 x 126 x 42 mm                                 |
| Weight                      | 1.8 kg  |
| Operating<br>Temp.<br>Range | 0~40 °C   |

| What's in<br>the Box | 1 x AD-200 main unit 1 x AD-200 control unit 1 x AD Switch DC 12V 1 x D-SUB cable, Male to MALE,Cable 1 x 3.5mm Stereo Cable, 1.2m 4 x 1U rack kit 16 x Screws M4 x 8mm |
|----------------------|---|
|----------------------|---|