

Auto Switch

聲像追蹤會議系統**VoiceTRX100**

Control	Web browser UI for configuration and control DVIP commands
Protocol	DVIP
Network Feature	1x RJ-45 Female (10/100/1000M Ethernet) DHCP/Static IP
POE	IEEE 802.3at PoE+
F/W Update	Automatic firmware upgrade
Power	Input AC 100~240V Switching Adaptor Output DC 12V / 1A
Video Output	2 x HDMI 2.0
Supported Video Outout Resolution	Up to 3840x2160p 60
Supported Video Switchers	iCast 10NDI series KMU-100+ SE-650 SE-1200MU SE-2600 series SE-3200 series SE-4000 series

Supported Microphones

Ai Speech MC-10A
Audio-Technica ATND1061
Audio-Technica ATUC-IR
Audio-Technica ATUC-50
Bosch DICENTIS Wireless
Bosch CCS-1000D
Relacart ACM-335
Relacart ACM-582
Sennheiser TCCM
Sennheiser TCC2
Shure MXW Microflex
Shure MXA-910
Shure MXA-920

USB Audio Mixers / Interfaces:

Allen and Heath CQ12T
Allen and Heath CQ18T
Zoom LiveTrak L6
Zoom LiveTrak L6 Max
Zoom LiveTrak L8
Zoom LiveTrak L12
RodeCaster Pro II
SoundCraft UI24R
M-Audio Duo
M-Audio Air 192|14
Tascam US-16X08
Tascam Mixcast 4
Behringer UMC404HD
Yamaha MGX12
Yamaha MGX16
Yamaha TF1 / TF3 / TF5
Yamaha DM3 / DM3S
Yamaha DM7 / DM7C